

BS THREE POLE NH FUSE SWITCH DISCONNECTORS

Three-phase fuse switch disconnectors for NH fuse-links. Available from size 000 to size 3 for board fixing and a mode size 00 for mounting on 60 mm busbar system. They provide IP20 protection against contacts and are manufactured in self-extinguishable materials.

www.df-sa.es/NH/fusebases/BS/

690V

NH000
100A

DESCRIPTION	REFERENCE	U (V)	PACKING
FUSE SWITCH DISCONNECTOR DIRECT CONNECTION	335005	690	1



NH00
160A


FUSE SWITCH DISCONNECTOR M8 SCREW CONNECTION	335025	690	1
FUSE SWITCH DISCONNECTOR Cu4-70mm ² CLAMP CONNECTION	335026	690	1



335026

NH00
160A

FUSE SWITCH DISCONNECTOR 60mm BUSBAR CONNECTION (Clamp or Screw for output connection)	335040	690	1
---	--------	-----	---



335040

NH1
250A

FUSE SWITCH DISCONNECTOR M10 SCREW CONNECTION	335095	690	1
---	--------	-----	---



NH2
400A

FUSE SWITCH DISCONNECTOR M10 SCREW CONNECTION	335155	690	1
---	--------	-----	---

NH3
630A

FUSE SWITCH DISCONNECTOR M12 SCREW CONNECTION	335195	690	1
---	--------	-----	---

STANDARDS
IEC 60269-1
IEC 60269-2
EN 60269-1
EN 60269-2
DIN 43620

APPROVALS
RoHS
compliant

TECHNICAL
DIMENSIONS

PAGE 44

TECHNICAL
TECHNICAL DATA

PAGE 44